


Maker Tape Battery Holders

Make your own battery holder with 3D printing and some Maker Tape.

Written By: Pete Prodoehl



INTRODUCTION


Make your own battery holder with 3D printing and some Maker Tape. This can be a fun project if you've got a 3D printed in your classroom and some of our Maker Tape on hand.

TOOLS:

- 3D Printer (1)
- Scissors (1)

PARTS:
Maker Tape (1)
1/4" Wide

Step 1 — Overview



- Circuits need power, and if you need a battery pack, or a convenient holder for a single AA or AAA battery, you can make your own as long as you've got a 3D printer and some Maker Tape.
- This project will provide files and demonstrate how to create your own battery pack, including how to create a conductive path for multiple batteries.
- Note! Like any project utilizing batteries there is some danger.
 Please read Step 2 for some warnings about working with these battery holders.


Step 2 — Warning!



- While this project is safe if done properly, it can also cause batteries to overheat, tape to burn, and plastic to melt.
- These battery packs are mean for educational purposes and should not be used *permanently* or without proper supervision.


- For safety it is recommended to remove the batteries from the holder when not being used in a circuit. Store them safely when not in use.
 - Do not stack battery holders while batteries are inserted!
 - Do not put battery holders into a bag or box when batteries are inserted!
 - Do not place battery holders on conductive surfaces such as a metal table.
- While **Maker Tape** is designed (and works perfect) for low-power circuits, it can only handle so many amps of power.
- Check out this video for more info: <u>Conductive Tape Destructive</u> <u>Testing</u>

Step 3 — Download and Print




- You can download the file and print it on your own 3D Printer.
- Find it in our GitHub repository: <u>https://github.com/BrownDogGadgets/3D-Pr...</u>
 - You can also find the files on Printables: <u>https://www.printables.com/model/232721-...</u>
- You'll find ready-to-print STL files for one, two, and three AAA and AA batteries.
- (i) There's also a .scad file so if you're comfortable editing <u>OpenSCAD</u> code you can also easily create versions that hold 4, 5, 6 or more batteries!

Step 4 — Add Maker Tape




- For the single battery holder you just need to add a piece of tape looped around each end so the positive and negative side of the battery will make contact with the tape when pressed in place.
- For multiple batteries you'll need to connect the negative of one battery to the positive of the next battery. This connects the batteries in **series**.
- (i) Tip! If your battery fits a bit too loose you can just add another layer of Maker Tape around the end of the holder for a tighter fit.

Step 5 — Add Batteries




- Once you have your tape (or tape paths) in place you can add the batteries.
- They should fit in snug so that the ends are touching the Maker Tape. (If they do not, you can just add another layer of tape.)
- Remember, Maker Tape is conductive on both sides and all the way through, so layering it works just fine. (This is not the case with most copper tapes.)

Step 6 — Add to Circuit



- You can use these battery packs in a circuit the same way you would use any battery pack.
- You can even use a tape loop to stick the battery pack right down to your Maker Tape pathways.

Step 7 — Take it Further



- Maybe you'll come up with some new ways to use these battery packs.
- Got some batteries that are down to just one volt? Put three of them in a holder together and you've got a 3 volt battery pack which is equal to a battery pack with two fresh batteries. A great way to get a bit more use out of old batteries.
- Could you connect the packs in parallel? Sure! It's just a matter of running Maker Tape for a specific pathway.
- One of our favorite uses is to pop one battery into a holder to check it with a multimeter. This solves the problem of trying to hold the battery and the meter probes at the same time.